

**MOBILE REPORTING MODULE EMPLOYING TIMING AND MESSAGE  
CONSOLIDATION TO ECONOMIZE TRANSMISSIONS**

**BACKGROUND OF THE INVENTION**

**I. Field of the Invention**

[0001] The present invention concerns a method for conserving wireless transmissions of a remote electronic reporting module to a monitoring facility. In order to reduce wireless transmissions of the remote module, the send time is used to convey added information. Also, when coverage is unknown, the remote module incorporates data with a coverage query in order to skip the need to subsequently transmit the data in the event the monitoring facility confirms coverage.

**II. Description of the Related Art**

[0002] QUALCOMM INCORPORATED has been in the trailer-tracking business for over a decade and has installed over 25,000 tethered TrailerTRACS® units that send trailer-management data via the OmniTRACS® mobile communications system. QUALCOMM also provides a cellular-untethered solution to complement the tethered product. Both products use stealth-mounted mobile communications technology to provide reporting of trailer location and operational events.

[0003] When a trailer is coupled to its tractor cab, the OmniTRACS/TrailerTRACS system provides features including (1) reporting positive tractor/trailer ID with every connect and disconnect, (2) providing real-time position reports, (3) recording events that occur with respect to the trailer, (4) recording various events' location, date, and time, and (5) the ability to upgrade feature sets in the field.

[0004] When the trailer is uncoupled from its tractor ("untethered"), nationwide cellular communications is provided using MICROBURST technology of AERIS.NET. In this condition, a TrailerTRACS unit sends automatic GPS-based trailer position reports, provides optional load sensor reports, tells whether the trailer is empty or not empty, reports door open/closed, and records each event's location, date, and time. Depending upon battery type and environmental factors, the TrailerTRACS unit can operate in its untethered state for at least one month. During this time the TrailerTRACS unit performs various power management and battery diagnostics.

K.V.G.  
 7/27/04  
 [0005] Although remote monitoring systems such as the <sup>OmniTRACS</sup>~~OMNITRACS~~ and <sup>TrailerTRACS</sup>~~TRAILERTRACS~~ products provide a significant advance and enjoy significant commercial success today, QUALCOMM engineers continually endeavor to improve the performance and efficiency of such mobile communications systems. Clearly, conservation of battery power is a concern since the TrailerTRACS product transmits messages even when the trailer is uncoupled to its tractor, and has no other power source. Accordingly, one area of possible focus among QUALCOMM development engineers is decreasing the number and length of messages transmitted by the TrailerTRACS product without sacrificing any richness in data reporting.

### SUMMARY OF THE INVENTION

4006  
 4007  
 4008  
 4009  
 4010  
 4011  
 4012  
 4013  
 4014  
 4015  
 4016  
 4017  
 4018  
 4019  
 4020  
 4021  
 4022  
 4023  
 4024  
 4025  
 4026  
 4027  
 4028  
 4029  
 4030  
 4031  
 4032  
 4033  
 4034  
 4035  
 4036  
 4037  
 4038  
 4039  
 4040  
 4041  
 4042  
 4043  
 4044  
 4045  
 4046  
 4047  
 4048  
 4049  
 4050  
 4051  
 4052  
 4053  
 4054  
 4055  
 4056  
 4057  
 4058  
 4059  
 4060  
 4061  
 4062  
 4063  
 4064  
 4065  
 4066  
 4067  
 4068  
 4069  
 4070  
 4071  
 4072  
 4073  
 4074  
 4075  
 4076  
 4077  
 4078  
 4079  
 4080  
 4081  
 4082  
 4083  
 4084  
 4085  
 4086  
 4087  
 4088  
 4089  
 4090  
 4091  
 4092  
 4093  
 4094  
 4095  
 4096  
 4097  
 4098  
 4099  
 4100  
 4101  
 4102  
 4103  
 4104  
 4105  
 4106  
 4107  
 4108  
 4109  
 4110  
 4111  
 4112  
 4113  
 4114  
 4115  
 4116  
 4117  
 4118  
 4119  
 4120  
 4121  
 4122  
 4123  
 4124  
 4125  
 4126  
 4127  
 4128  
 4129  
 4130  
 4131  
 4132  
 4133  
 4134  
 4135  
 4136  
 4137  
 4138  
 4139  
 4140  
 4141  
 4142  
 4143  
 4144  
 4145  
 4146  
 4147  
 4148  
 4149  
 4150  
 4151  
 4152  
 4153  
 4154  
 4155  
 4156  
 4157  
 4158  
 4159  
 4160  
 4161  
 4162  
 4163  
 4164  
 4165  
 4166  
 4167  
 4168  
 4169  
 4170  
 4171  
 4172  
 4173  
 4174  
 4175  
 4176  
 4177  
 4178  
 4179  
 4180  
 4181  
 4182  
 4183  
 4184  
 4185  
 4186  
 4187  
 4188  
 4189  
 4190  
 4191  
 4192  
 4193  
 4194  
 4195  
 4196  
 4197  
 4198  
 4199  
 4200  
 4201  
 4202  
 4203  
 4204  
 4205  
 4206  
 4207  
 4208  
 4209  
 4210  
 4211  
 4212  
 4213  
 4214  
 4215  
 4216  
 4217  
 4218  
 4219  
 4220  
 4221  
 4222  
 4223  
 4224  
 4225  
 4226  
 4227  
 4228  
 4229  
 4230  
 4231  
 4232  
 4233  
 4234  
 4235  
 4236  
 4237  
 4238  
 4239  
 4240  
 4241  
 4242  
 4243  
 4244  
 4245  
 4246  
 4247  
 4248  
 4249  
 4250  
 4251  
 4252  
 4253  
 4254  
 4255  
 4256  
 4257  
 4258  
 4259  
 4260  
 4261  
 4262  
 4263  
 4264  
 4265  
 4266  
 4267  
 4268  
 4269  
 4270  
 4271  
 4272  
 4273  
 4274  
 4275  
 4276  
 4277  
 4278  
 4279  
 4280  
 4281  
 4282  
 4283  
 4284  
 4285  
 4286  
 4287  
 4288  
 4289  
 4290  
 4291  
 4292  
 4293  
 4294  
 4295  
 4296  
 4297  
 4298  
 4299  
 4300  
 4301  
 4302  
 4303  
 4304  
 4305  
 4306  
 4307  
 4308  
 4309  
 4310  
 4311  
 4312  
 4313  
 4314  
 4315  
 4316  
 4317  
 4318  
 4319  
 4320  
 4321  
 4322  
 4323  
 4324  
 4325  
 4326  
 4327  
 4328  
 4329  
 4330  
 4331  
 4332  
 4333  
 4334  
 4335  
 4336  
 4337  
 4338  
 4339  
 4340  
 4341  
 4342  
 4343  
 4344  
 4345  
 4346  
 4347  
 4348  
 4349  
 4350  
 4351  
 4352  
 4353  
 4354  
 4355  
 4356  
 4357  
 4358  
 4359  
 4360  
 4361  
 4362  
 4363  
 4364  
 4365  
 4366  
 4367  
 4368  
 4369  
 4370  
 4371  
 4372  
 4373  
 4374  
 4375  
 4376  
 4377  
 4378  
 4379  
 4380  
 4381  
 4382  
 4383  
 4384  
 4385  
 4386  
 4387  
 4388  
 4389  
 4390  
 4391  
 4392  
 4393  
 4394  
 4395  
 4396  
 4397  
 4398  
 4399  
 4400  
 4401  
 4402  
 4403  
 4404  
 4405  
 4406  
 4407  
 4408  
 4409  
 4410  
 4411  
 4412  
 4413  
 4414  
 4415  
 4416  
 4417  
 4418  
 4419  
 4420  
 4421  
 4422  
 4423  
 4424  
 4425  
 4426  
 4427  
 4428  
 4429  
 4430  
 4431  
 4432  
 4433  
 4434  
 4435  
 4436  
 4437  
 4438  
 4439  
 4440  
 4441  
 4442  
 4443  
 4444  
 4445  
 4446  
 4447  
 4448  
 4449  
 4450  
 4451  
 4452  
 4453  
 4454  
 4455  
 4456  
 4457  
 4458  
 4459  
 4460  
 4461  
 4462  
 4463  
 4464  
 4465  
 4466  
 4467  
 4468  
 4469  
 4470  
 4471  
 4472  
 4473  
 4474  
 4475  
 4476  
 4477  
 4478  
 4479  
 4480  
 4481  
 4482  
 4483  
 4484  
 4485  
 4486  
 4487  
 4488  
 4489  
 4490  
 4491  
 4492  
 4493  
 4494  
 4495  
 4496  
 4497  
 4498  
 4499  
 4500  
 4501  
 4502  
 4503  
 4504  
 4505  
 4506  
 4507  
 4508  
 4509  
 4510  
 4511  
 4512  
 4513  
 4514  
 4515  
 4516  
 4517  
 4518  
 4519  
 4520  
 4521  
 4522  
 4523  
 4524  
 4525  
 4526  
 4527  
 4528  
 4529  
 4530  
 4531  
 4532  
 4533  
 4534  
 4535  
 4536  
 4537  
 4538  
 4539  
 4540  
 4541  
 4542  
 4543  
 4544  
 4545  
 4546  
 4547  
 4548  
 4549  
 4550  
 4551  
 4552  
 4553  
 4554  
 4555  
 4556  
 4557  
 4558  
 4559  
 4560  
 4561  
 4562  
 4563  
 4564  
 4565  
 4566  
 4567  
 4568  
 4569  
 4570  
 4571  
 4572  
 4573  
 4574  
 4575  
 4576  
 4577  
 4578  
 4579  
 4580  
 4581  
 4582  
 4583  
 4584  
 4585  
 4586  
 4587  
 4588  
 4589  
 4590  
 4591  
 4592  
 4593  
 4594  
 4595  
 4596  
 4597  
 4598  
 4599  
 4600  
 4601  
 4602  
 4603  
 4604  
 4605  
 4606  
 4607  
 4608  
 4609  
 4610  
 4611  
 4612  
 4613  
 4614  
 4615  
 4616  
 4617  
 4618  
 4619  
 4620  
 4621  
 4622  
 4623  
 4624  
 4625  
 4626  
 4627  
 4628  
 4629  
 4630  
 4631  
 4632  
 4633  
 4634  
 4635  
 4636  
 4637  
 4638  
 4639  
 4640  
 4641  
 4642  
 4643  
 4644  
 4645  
 4646  
 4647  
 4648  
 4649  
 4650  
 4651  
 4652  
 4653  
 4654  
 4655  
 4656  
 4657  
 4658  
 4659  
 4660  
 4661  
 4662  
 4663  
 4664  
 4665  
 4666  
 4667  
 4668  
 4669  
 4670  
 4671  
 4672  
 4673  
 4674  
 4675  
 4676  
 4677  
 4678  
 4679  
 4680  
 4681  
 4682  
 4683  
 4684  
 4685  
 4686  
 4687  
 4688  
 4689  
 4690  
 4691  
 4692  
 4693  
 4694  
 4695  
 4696  
 4697  
 4698  
 4699  
 4700  
 4701  
 4702  
 4703  
 4704  
 4705  
 4706  
 4707  
 4708  
 4709  
 4710  
 4711  
 4712  
 4713  
 4714  
 4715  
 4716  
 4717  
 4718  
 4719  
 4720  
 4721  
 4722  
 4723  
 4724  
 4725  
 4726  
 4727  
 4728  
 4729  
 4730  
 4731  
 4732  
 4733  
 4734  
 4735  
 4736  
 4737  
 4738  
 4739  
 4740  
 4741  
 4742  
 4743  
 4744  
 4745  
 4746  
 4747  
 4748  
 4749  
 4750  
 4751  
 4752  
 4753  
 4754  
 4755  
 4756  
 4757  
 4758  
 4759  
 4760  
 4761  
 4762  
 4763  
 4764  
 4765  
 4766  
 4767  
 4768  
 4769  
 4770  
 4771  
 4772  
 4773  
 4774  
 4775  
 4776  
 4777  
 4778  
 4779  
 4780  
 4781  
 4782  
 4783  
 4784  
 4785  
 4786  
 4787  
 4788  
 4789  
 4790  
 4791  
 4792  
 4793  
 4794  
 4795  
 4796  
 4797  
 4798  
 4799  
 4800  
 4801  
 4802  
 4803  
 4804  
 4805  
 4806  
 4807  
 4808  
 4809  
 4810  
 4811  
 4812  
 4813  
 4814  
 4815  
 4816  
 4817  
 4818  
 4819  
 4820  
 4821  
 4822  
 4823  
 4824  
 4825  
 4826  
 4827  
 4828  
 4829  
 4830  
 4831  
 4832  
 4833  
 4834  
 4835  
 4836  
 4837  
 4838  
 4839  
 4840  
 4841  
 4842  
 4843  
 4844  
 4845  
 4846  
 4847  
 4848  
 4849  
 4850  
 4851  
 4852  
 4853  
 4854  
 4855  
 4856  
 4857  
 4858  
 4859  
 4860  
 4861  
 4862  
 4863  
 4864  
 4865  
 4866  
 4867  
 4868  
 4869  
 4870  
 4871  
 4872  
 4873  
 4874  
 4875  
 4876  
 4877  
 4878  
 4879  
 4880  
 4881  
 4882  
 4883  
 4884  
 4885  
 4886  
 4887  
 4888  
 4889  
 4890  
 4891  
 4892  
 4893  
 4894  
 4895  
 4896  
 4897  
 4898  
 4899  
 4900  
 4901  
 4902  
 4903  
 4904  
 4905  
 4906  
 4907  
 4908  
 4909  
 4910  
 4911  
 4912  
 4913  
 4914  
 4915  
 4916  
 4917  
 4918  
 4919  
 4920  
 4921  
 4922  
 4923  
 4924  
 4925  
 4926  
 4927  
 4928  
 4929  
 4930  
 4931  
 4932  
 4933  
 4934  
 4935  
 4936  
 4937  
 4938  
 4939  
 4940  
 4941  
 4942  
 4943  
 4944  
 4945  
 4946  
 4947  
 4948  
 4949  
 4950  
 4951  
 4952  
 4953  
 4954  
 4955  
 4956  
 4957  
 4958  
 4959  
 4960  
 4961  
 4962  
 4963  
 4964  
 4965  
 4966  
 4967  
 4968  
 4969  
 4970  
 4971  
 4972  
 4973  
 4974  
 4975  
 4976  
 4977  
 4978  
 4979  
 4980  
 4981  
 4982  
 4983  
 4984  
 4985  
 4986  
 4987  
 4988  
 4989  
 4990  
 4991  
 4992  
 4993  
 4994  
 4995  
 4996  
 4997  
 4998  
 4999  
 5000  
 5001  
 5002  
 5003  
 5004  
 5005  
 5006  
 5007  
 5008  
 5009  
 5010  
 5011  
 5012  
 5013  
 5014  
 5015  
 5016  
 5017  
 5018  
 5019  
 5020  
 5021  
 5022  
 5023  
 5024  
 5025  
 5026  
 5027  
 5028  
 5029  
 5030  
 5031  
 5032  
 5033  
 5034  
 5035  
 5036  
 5037  
 5038  
 5039  
 5040  
 5041  
 5042  
 5043  
 5044  
 5045  
 5046  
 5047  
 5048  
 5049  
 5050  
 5051  
 5052  
 5053  
 5054  
 5055  
 5056  
 5057  
 5058  
 5059  
 5060  
 5061  
 5062  
 5063  
 5064  
 5065  
 5066  
 5067  
 5068  
 5069  
 5070  
 5071  
 5072  
 5073  
 5074  
 5075  
 5076  
 5077  
 5078  
 5079  
 5080  
 5081  
 5082  
 5083  
 5084  
 5085  
 5086  
 5087  
 5088  
 5089  
 5090  
 5091  
 5092  
 5093  
 5094  
 5095  
 5096  
 5097  
 5098  
 5099  
 5100  
 5101  
 5102  
 5103  
 5104  
 5105  
 5106  
 5107  
 5108  
 5109  
 5110  
 5111  
 5112  
 5113  
 5114  
 5115  
 5116  
 5117  
 5118  
 5119  
 5120  
 5121  
 5122  
 5123  
 5124  
 5125  
 5126  
 5127  
 5128  
 5129  
 5130  
 5131  
 5132  
 5133  
 5134  
 5135  
 5136  
 5137  
 5138  
 5139  
 5140  
 5141  
 5142  
 5143  
 5144  
 5145  
 5146  
 5147  
 5148  
 5149  
 5150  
 5151  
 5152  
 5153  
 5154  
 5155  
 5156  
 5157  
 5158  
 5159  
 5160  
 5161  
 5162  
 5163  
 5164  
 5165  
 5166  
 5167  
 5168  
 5169  
 5170  
 5171  
 5172  
 5173  
 5174  
 5175  
 5176  
 5177  
 5178  
 5179  
 5180  
 5181  
 5182  
 5183  
 5184  
 5185  
 5186  
 5187  
 5188  
 5189  
 5190  
 5191  
 5192  
 5193  
 5194  
 5195  
 5196  
 5197  
 5198  
 5199  
 5200  
 5201  
 5202  
 5203  
 5204  
 5205  
 5206  
 5207  
 5208  
 5209  
 5210  
 5211  
 5212  
 5213  
 5214  
 5215  
 5216  
 5217  
 5218  
 5219  
 5220  
 5221  
 5222  
 5223  
 5224  
 5225  
 5226  
 5227  
 5228  
 5229  
 5230  
 5231  
 5232  
 5233  
 5234  
 5235  
 5236  
 5237  
 5238  
 5239  
 5240  
 5241  
 5242  
 5243  
 5244  
 5245  
 5246  
 5247  
 5248  
 5249  
 5250  
 5251  
 5252  
 5253  
 5254  
 5255  
 5256  
 5257  
 5258  
 5259  
 5260  
 5261  
 5262  
 5263  
 5264  
 5265  
 5266  
 5267  
 5268  
 5269  
 5270  
 5271  
 5272  
 5273  
 5274  
 5275  
 5276  
 5277  
 5278  
 5279  
 5280  
 5281  
 5282  
 5283  
 5284  
 5285  
 5286  
 5287  
 5288  
 5289  
 5290  
 5291  
 5292  
 5293  
 5294  
 5295  
 5296  
 5297  
 5298  
 5299  
 5300  
 5301  
 5302  
 5303  
 5304  
 5305  
 5306  
 5307  
 5308  
 5309  
 5310  
 5311  
 5312  
 5313  
 5314  
 5315  
 5316  
 5317  
 5318  
 5319  
 5320  
 5321  
 5322  
 5323  
 5324  
 5325  
 5326  
 5327  
 5328  
 5329  
 5330  
 5331  
 5332  
 5333  
 5334  
 5335  
 5336  
 5337  
 5338  
 5339  
 5340  
 5341  
 5342  
 5343  
 5344  
 53

signal-bearing medium tangibly embodying a program of machine-readable instructions executable by a digital data processing apparatus to conduct operations as discussed herein. Another embodiment concerns logic circuitry having multiple interconnected electrically conductive elements configured to conduct operations as discussed herein.

[0009] The invention affords its users with a number of distinct advantages. Chiefly, by reducing the length and number of transmissions from mobile reporting modules to their monitoring facility, the invention saves the mobile reporting module's valuable battery power. This also has the effect of reducing any congestion of communications frequencies. The invention also provides a number of other advantages and benefits, which should be apparent from the following description of the invention.

### BRIEF DESCRIPTION OF THE DRAWINGS

[0010] FIGURE 1 is a block diagram of the hardware components and interconnections of the hardware environment of the invention.

[0011] FIGURE 2 is a block diagram of a digital data processing machine according to the invention.

[0012] FIGURE 3 shows an exemplary signal-bearing medium according to the invention.

[0013] FIGURE 4 is a flowchart of an operating sequence for registration timing to convey coverage evaluation, according to the invention.

[0014] FIGURE 5 is a flowchart of an operating sequence for consolidating data with coverage query transmission under unknown coverage conditions, according to the invention.

### DETAILED DESCRIPTION

[0015] The nature, objectives, and advantages of the invention will become more apparent to those skilled in the art after considering the following detailed description in connection with the accompanying drawings.

### HARDWARE COMPONENTS & INTERCONNECTIONS

#### Hardware Environment

[0016] FIGURE 1 depicts an exemplary hardware environment 100 for use of the present invention. A mobile reporting module 106 prepares various status messages concerning the status of some

equipment being monitored by the module 106. The mobile reporting module 106 comprises an electronic module with some computing capability, and may be implemented in various forms as discussed below. In the illustrated example, the mobile reporting module 106 is installed at a freight truck 104 having a trailer 105, although freight trucks are merely one example, as the mobile reporting module 106 may be implemented to monitor other types of equipment.

[0017] The mobile reporting module 106 includes one or more sensors 106b to monitor conditions of the trailer 105 and the module 106 itself such as: door open/close event, cargo events, latitude, longitude, battery condition or tampering, condition of the module 106, software version of the module 106, etc. The sensors 106b may comprise sensors as utilized in the commercially available ~~TrailerTRACS~~ <sup>TrailerTRACS</sup> system of QUALCOMM, INC. Some exemplary types of sensors 106b include global positioning system (GPS) units, door ajar sensors, acoustic cargo sensors, motion detectors, voltage/current sensors, etc.

[0018] Another component of the module 106 is a local clock 188. The clock 188 comprises a battery-driven timer, and may be implemented by known varieties of timing devices. The mobile reporting module 106 also includes a transceiver 106a, for exchanging messages with a message processing facility 108 via a communication network 102. As an example, the transceiver 106a may comprise equipment as found in the TrailerTRACS product of Qualcomm Incorporated. When the mobile module 106 initiates a communication, it is coupled to the network 102 by a wireless connection 110. The network 102 completes the call by forming another connection 112 (wireless or otherwise) coupling the call processing facility 108 to the network 102. The call processing facility 108 includes computing equipment to receive, interpret, and otherwise process incoming calls from mobile reporting modules 106.

[0019] The mobile reporting module 106 additionally includes a storage device 107 for storing various information pertaining to the ~~operation~~ <sup>operation</sup> of module 106, including a coverage record. The coverage record contains information indicating whether or not a particular geographic area is covered by a wireless service provider, such as a cellular telephone service provider. Each mobile reporting module 106 maintains such a record, based on a historical success or failure of communications with various networks 102, as to whether coverage has been arranged with such networks. Each network identifies itself by broadcasting a "coverage code", which is received by module 106 compared to the coverage record. The coverage record may indicate that the just-received coverage code corresponds to an area which is known to have "good" coverage, no coverage, or that the status of coverage is unknown, based upon previous results of communication

efforts by module 106 in the past.

[0020] An example of the coverage record appears below in TABLE 1. In this example, due to previous success in communicating with the facility 108 via the network identified by coverage code A01, the mobile reporting module 106 has self-noted this network coverage as being "good." Due to a previous failure in communicating with the network identified by coverage code A02, the module 106 has marked this network coverage as "bad." Not having communicated previously with the network identified by coverage code A99, the module 106 has marked this coverage as "unknown," which is a default value for the entire table.

COVERAGE CODE	HISTORICAL SIGNIFICANCE OF COVERAGE CODE		
	GOOD	BAD	UNKNOWN
A01	X		
A02		X	
...			
A99			X

TABLE 1 - EXEMPLARY EMPIRICAL COVERAGE RECORD

[0021] Although other approaches may be used, the environment 100 may avoid the costs of a full-blown voice cellular service by utilizing a network 102 with specialized facilities for conducting brief, non-voice transmissions. One example is the MICROBURST technology developed by AERIS.NET, INC. of San Jose, California. The MICROBURST technology is a commercially available product for sending short data packets over the control channels of existing cellular networks, and provides an economical conduit between the cellular infrastructure and remote data transceivers, such as module 106. MICROBURST coverage is dictated by agreements with cellular companies and then coordinates distribution channels, such as service providers with vertical market

expertise, to take advantage of an evolving nationwide, virtual network. AERIS.NET maintains and operates the virtual network and a nationwide MICROBURST hub, which acts as the network intelligence. The AERIS service, among other benefits, enables the mobile reporting units 106 to communicate with the facility 108 using a cellular transceiver, but without the need to occupy any voice channels.

[0022] Facilities of the call processing facility 108 include computing equipment to receive, interpret, and act upon messages transmitted by the mobile reporting module 110. In one embodiment, the facility 108 includes a local clock 120.

#### Exemplary Digital Data Processing Apparatus

[0023] As mentioned above, the mobile reporting module 106 and monitoring facility 108 may be implemented in various forms. As one example, each of these components may comprise a digital data processing apparatus, as exemplified by the hardware components and interconnections of the digital data processing apparatus 200 of FIGURE 2.

[0024] The apparatus 200 includes a processor 202, such as a microprocessor or other processing machine, coupled to a storage 204. In the present example, the storage 204 includes a fast-access storage 206, as well as nonvolatile storage 208. The fast-access storage 206 may comprise random access memory ("RAM"), and may be used to store the programming instructions executed by the processor 202. The nonvolatile storage 208 may comprise, for example, one or more magnetic data storage disks such as a "hard drive", a tape drive, or any other suitable storage device for storing the programming instructions, as well as other types of data necessary for the operation of apparatus 200. The apparatus 200 also includes an input/output 210, such as a line, bus, cable, electromagnetic link, or other means for the processor 202 to exchange data with other hardware external to the apparatus 200.

[0025] Despite the specific foregoing description, ordinarily skilled artisans (having the benefit of this disclosure) will recognize that the apparatus discussed above may be implemented in a machine of different construction, without departing from the scope of the invention. As a specific example, one of the components 206, 208 may be eliminated; furthermore, the storage 204 may be provided on-board the processor 202, or even provided externally to the apparatus 200.

#### Logic Circuitry

[0026] In contrast to the digital data processing apparatus discussed above, a different embodiment

of the invention uses logic circuitry instead of computer-executed instructions to implement the mobile reporting module. Depending upon the particular requirements of the application in the areas of speed, expense, tooling costs, and the like, this logic may be implemented by constructing an application-specific integrated circuit ("ASIC") having thousands of tiny integrated transistors. Such an ASIC may be implemented with CMOS, TTL, VLSI, or another suitable construction. Other alternatives include a digital signal processing chip ("DSP"), discrete circuitry (such as resistors, capacitors, diodes, inductors, and transistors), field programmable gate array ("FPGA"), programmable logic array ("PLA"), and the like.

### OPERATION

[0027]

Having described the structural features of the present invention, the method aspect of the present invention will now be described. As mentioned above, the method aspect of the invention generally involves the wireless transmission of reports, messages, and data from various mobile reporting modules to a monitoring facility, and more particularly, various techniques to reduce the number and time of these transmissions. Although the present invention has broad applicability to data collection systems, the specifics of the structure that has been described is particularly suited for use by mobile monitoring stations for sensing the condition of freight trailers and their cargo and providing representative reports to the monitoring facility via wireless communications networks, and the explanation that follows will emphasize such an application of the invention without any intended limitation.

#### Signal-Bearing Media

[0028]

In the context of FIGURE 1, such a method may be implemented, for example, by operating the mobile reporting module 106 and monitoring facility 108, each as embodied by a digital data processing apparatus 200, to execute respective sequences of machine-readable instructions. These instructions may reside in various types of signal-bearing media. In this respect, one aspect of the present invention concerns signal-bearing media embodying programs of machine-readable instructions executable by digital data processors to perform the functions of the mobile reporting module 106 and monitoring facility 108 as described herein.

[0029]

This signal-bearing media may comprise, for example, RAM (not shown), as represented by the fast-access storage 206. Alternatively, the instructions may be contained in another signal-

bearing media, such as a magnetic data storage diskette 300 (FIGURE 3), directly or indirectly accessible by the processor 202. Whether contained in the storage 206, diskette 300, or elsewhere, the instructions may be stored on a variety of machine-readable data storage media. Some examples include as direct access storage (e.g., a conventional "hard drive", redundant array of inexpensive disks ("RAID")), or another direct access storage device ("DASD")), serial-access storage such as magnetic or optical tape, electronic read-only memory (e.g., ROM, EPROM, or EEPROM), optical storage (e.g., CD-ROM, WORM, DVD, digital optical tape), paper "punch" cards, or other suitable signal-bearing media including analog or digital transmission media and analog and communication links and wireless. In an illustrative embodiment of the invention, the machine-readable instructions may comprise software object code, compiled from a language such as "C," etc.

### Logic Circuitry

[0030] In contrast to the signal-bearing medium discussed above, the method aspect of the invention may be implemented using logic circuitry, without using a processor to execute instructions. In this embodiment, the logic circuitry is implemented in the mobile reporting module 106 and/or monitoring facility 108, and is configured to perform operations to implement the method of the invention. The logic circuitry may be implemented using many different types of circuitry, as discussed above.

### Operating Sequence- Transmission Timing

[0031] FIGURE 4 shows a sequence 400 to illustrate one example of the method aspect of the present invention. This sequence 400 describes a process for communications between a mobile reporting module 106 and a monitoring facility 108, where the send time of certain messages is used to convey added information. For ease of explanation, but without any intended limitation, the example of FIGURE 4 is described in the context of FIGURES 1-3, described above.

[0032] In step 401, the module 106 and monitoring facility 108 prearrange the significance of various reporting times to be used in future reports by the module 106. Namely, to save transmission time and bandwidth, certain additional information will be assumed according to the time at which the module 106 reports to the facility 108. The prearrangement of step 401 includes various aspects affecting the significance of future reports, such as:



1. Whether the facility 108 will take the reporting time to be the time of the clock 188, in which case the module 106 includes this time in the message, or whether the clock 188 is pre-synchronized with the clock 120 at the facility 108.
2. Which messages will utilize reporting time to convey additional information. In the illustrated example, only "registration" messages are used in this fashion.
3. What significance is assigned to which times. In the illustrated examples, reporting times occurring at even minutes after the hour (such as 12:42) mean that the module 106 deems coverage by the network 102 to be "good," whereas reporting times occurring at odd minutes after the hour (such as 12:57) mean that the module 106 deems coverage to be "unknown." In the present example, the presence of "coverage" means that the module 106 is within range of a network's cellular communication equipment; the module's transceiver 106a is approved, contracted, or otherwise subscribed to that network; and that the MICROBURST system of AERIS.NET is operable in this network, as described above.

[0033] In step 402, the mobile reporting module 106 wakes. This may occur due to a previous power-off, re-boot, software reset, or other such condition. After step <sup>402</sup>~~404~~, the module 106 "listens" to broadcasts of the network 102 (step 404), since the identity of the surrounding cellular network 102 changes as the module 106 travels. As the identity of the networks changes, so does coverage, since financial arrangements might (or might not) have been made with each network to provide communications coverage to the module 106. The module 106 monitors broadcasts from the network 102 for a coverage code, which may also be known in the art as a "SID," or a System Identification code, etc.

[0034] When a coverage code is received, module 106 analyzes coverage by referencing this coverage code against the coverage record 107 to determine whether the current coverage code indicates good, bad, or unknown coverage (step 405). Step 406 proceeds accordingly. Namely, if coverage is good, processing advances to step 408, where the mobile unit 106 (optionally) determines whether certain registration criteria have been met. For instance, these criteria may include a review of whether the module 106 has already registered its presence with the network 102. If the registration criteria are not met, the routine 400 returns to step 404. Otherwise, if registration is warranted, processing proceeds to step 410, where the module 106 transmits a registration message. The registration message functions to inform the cellular infrastructure of the general location and availability of module 106. To serve this purpose, the registration message generally includes an

identifier (ID) of the module 106 at minimum, and may include further information such as a mobile identification number (MIN), electronic serial number (ESN), or other information generally known by those skilled in the art. Importantly, the module 106 transmits the registration message during an even minute past the hour, such as 6:36 as indicated by the clock 188. If the facility 108 lacks the clock 120, or does not have the clock 120 synchronized with the clock 188, the registration message includes the registration time according to the clock 188.

[0035] After step 410, the facility 108 receives then analyzes the registration message received from the module 106 (step 412). Particularly, the facility 108 determines by its content that the message concerns registration, and by its transmission time that it indicates known good coverage. The facility 108 takes the time of receiving the message according to its own clock 120 (if so equipped) as the transmission time, or alternatively the time imprinted upon the message by the module 106. Since the reporting time of the message indicates known good coverage, the facility 108 refrains from sending any acknowledgment ("ack"), conserving transmission bandwidth for other messages.

[0036] In contrast to the foregoing, step 406 returns to step 404 if the current state of coverage is "bad." If coverage is "unknown," processing advances to step 414, where the module 106 transmits a registration message. Importantly, the module 106 transmits the registration message during an odd minute past the hour, such as 6:37 as indicated by the clock 188; this differentiates from registration messages under conditions of "good" coverage. If the facility 108 lacks the clock 120 or does not have the clock synchronized with the clock 188, the registration message of step 414 includes the registration time according to the clock 188. After step 414, the facility 108 receives then analyzes the registration message received from the module 106 (step 416). Particularly, the facility 108 determines by its content that the message concerns registration, and by its transmission time that it indicates "unknown" coverage availability. The facility 108 takes the time of receiving the message according to its own clock 120 (if so equipped) as the transmission time, or alternatively the time imprinted upon the message by the module 106. Since the message's reporting time indicates unknown coverage availability, the facility 108 returns an acknowledge message confirming that coverage is good. In response, the module 106 may update the coverage record to associate the coverage code (from step 404) with "good" coverage (step 418). After step 418, the routine 400 returns to step 404.

#### Operating Sequence- Appending Data to Coverage Query

[0037] FIGURE 5 shows a sequence 500 to illustrate another example of the method aspect of the

present invention. This sequence 500 describes a process for communications between mobile reporting modules (such as 106) and the monitoring facility 108, where the remote module responds to unknown coverage by combining data with a coverage query in order to reduce the number of messages sent, and to save the need to subsequently transmit the data in the event the monitoring facility confirms coverage. For ease of explanation, but without any intended limitation, the example of FIGURE 5 is described in the context of FIGURES 1-3, described above.

[0038] In step 502, an "event" occurs requiring the module 106 to transmit a message reporting the event to the facility 108. Events requiring reporting are prearranged by programming of the module 106, and may include various particulars as to trailer empty or not empty, report door open/closed, battery condition, GPS position, etc. Accordingly, the message may include status messages as well as data. After step 502, the module 106 monitors broadcasts from the network 102 for a coverage code, in the manner discussed above (step 404, FIGURE 4).

[0039] When a coverage code is received, the module 106 analyzes coverage by referencing this coverage code against the coverage record to determine whether the current coverage code indicates good, bad, or unknown coverage (step 506). Then, if coverage is good, step 506 advances to step 508, where the mobile unit 106 transmits a representation of the event of step 502 and any related data. After step 508, the routine 500 ends in step 518.

[0040] In contrast to the foregoing, if coverage is known "bad," step 506 proceeds to step 510, where the module 106 waits for coverage to resume. If coverage is "unknown," step 506 advances to step 512, where the module 106 transmits a coverage query with a message representing the event of step 502 and any related data. Transmitting the coverage query with this message reduces number of transmissions from module 106 resulting in lower transmission costs and savings in battery power.

[0041] In one embodiment, the coverage query may be represented by a component of the message itself. For instance, if the status message comprises a binary code representing status conditions (e.g., trailer empty or not empty, report door open/closed, battery condition, etc. ), the coverage query may be included as a status bit in this binary status message. Alternatively, if the number of bits in the code are limited, the coverage query may be combined with other status items. As an example, the second bit in the code may indicate "coverage query plus door open" if binary "one."

[0042] After step 512, the module 106 asks whether an ack has been received from the facility 108. If not, this means that the coverage query has not been answered, and the module 106 proceeds to step 510. In this case, coverage remains unknown. On the other hand, if the message of step 512 is acknowledged, this means that coverage is confirmed and the facility 108 has confirmed receipt of

[illegible]

## OTHER EMBODIMENTS

**I CLAIM:**